

Registration No. :

--	--	--	--	--	--	--	--	--	--

Total number of printed pages – 2

B. Tech  
PCEE 4304

Sixth Semester Regular Examination – 2014

COMMUNICATION ENGINEERING

BRANCH : EEE

QUESTION CODE : F 236

Full Marks – 70

Time : 3 Hours

Answer Question No. 1 which is compulsory and any **five** from the rest.

The figures in the right-hand margin indicate marks.



1. Answer the following questions :

2 × 10

- State the conditions under which a given signal is Fourier transformable. What is the Fourier transform of an eternal sinusoid ?
- Give examples of two orthonormal functions. Prove their orthonormality.
- What is (are) the difference(s) between the spectrum of a rectangular pulse and that of a rectangular pulse train.
- Draw the phase spectrum of a rectangular pulse train. What information does it convey ?
- Give the low-pass to band-pass transformation of a signal and sketch it.
- What is a pilot tone ? Why is it used ?
- What is balanced in a balanced modulator ?
- Is FM a linear modulation scheme ? Justify.
- What is the physical reason for making a slope detector being used as an FM detector ?
- Which part of the spectrum is used as the standard AM broadcast band ? Cite at least two reasons.

P.T.O.

2. (a) Explain the need of an RF amplifier as the front end in a standard AM broadcast receiver with a suitable example. Is it essential? 5
- (b) An angle-modulated signal has the form  $u(t) = 100 \cos[2\pi f_c t + 4 \sin 2\pi f_m t]$  where  $f_c = 10$  MHz and  $f_m = 1$  kHz. Assuming this to be an FM signal, determine the modulation index and the transmitted signal bandwidth. Give the expression for the corresponding phase modulated signal. 5
3. (a) Explain the need for an interlaced scanning in TV broadcast. Sketch appropriate sketches. 5
- (b) Let a carrier be given by  $c(t) = 10 \cos(2\pi f_c t)$  and the message signal be  $\cos[20\pi t]$ . The message signal frequency modulates the carrier with  $k_f = 50$ . Find an expression for the modulated signal and determine how many harmonics should be selected to contain 99% of the modulated signal power. 5
4. Compare the square-law modulator and the switching modulator used for generating AM signals. 10
5. (a) Give the Fourier transform of a signal given as  $x(t) = \sum_{n=-\infty}^{\infty} (-1)^n \delta(t - nT)$ . Sketch the magnitude spectrum. 5
- (b) Give the Fourier transform of a signal given as  $x(t) = \pi(t-3) + \pi(t+3)$  where  $\pi(t)$  is a rectangular pulse of unit width. Sketch the magnitude spectrum. 5
6. (a) Show that a signal  $x(t)$  and its Hilbert transform  $\hat{x}(t)$  are orthogonal. 5
- (b) Show that the set of orthogonal signals  $\{\phi_n(t)\}_{n=-\infty}^{\infty}$  where  $\phi_n = \text{sinc}(2Wt - n)$  represent an orthogonal signal set. 5
7. (a) Compare the three types of sampling. Sketch the sampled waveforms in each case assuming the message signal to be a sinusoid. 5
- (b) How do you realize a PCM signal from a PAM signal? Show the steps very clearly. 5
8. Write short notes on any **two** : 5×2
- (a) Fourier transform of periodic signals
- (b) Balanced discriminator
- (c) Companding
- (d) Communication channels.